

Watts Hydroguard Filtration



Three easy steps to cleaner water

Watts™ Hydroguard™ is a residential water filtration unit, suitable for mains supply or rainwater harvesting, that provides sediment, CTO (Chlorine, Taste and Odour) and Ultraviolet filtration to remove contaminants, odour and bacteria to make water safe for your home.

The Hydroguard range features both 10 and 20-inch filters with or without UV filtration to offer the correct level of protection for your home and budget.

Components

Pre-assembled unit for easy assembly

High quality, NSF-certified filter cartridges.

Automatic UV lamp life countdown and replacement alarm

Weather-proof enclosure with lockable lid for safety and tamper proofing (UV models)

Stainless Steel fittings for extra strength and reliability



For more information on this product scan the QR code or visit hydroflow.co.nz



Product Information

Hydroflow Code	HG210	HG220	HG210UV	HG220UV
Water Supply	1-40°C water only from tank, bore or mains supply			
Ambient Temperature	1-40°C			
Inlet/Outlet Connections	25mm (1") BSP			
Electrical Input	N/A		230VAC / 50Hz	
Working Pressure	≤500kPa			
Maximum Pressure	800kPa			
Max Flow Rate	110 L/min (500kPa supply pressure)		95 L/min (500kPa supply pressure)	
Product Weight (No Water)	6.5 kg	12.5 kg	16 kg	21 kg
Product Weight (With Water)	12.5 kg	23.5 kg	24 kg	34 kg
Product Size (H x W x D)	520 x 405 x 220 mm	670 x 405 x 220 mm	630 x 640 x 230 mm	750 x 640 x 230 mm

Spares & Consumables

HG210		HG220		HG210UV		HG220UV	
HGFH10	Filter Housing 10"	HGFH20	Filter Housing 20"	HGFH10	Filter Housing 10"	HGFH20	Filter Housing 20"
HG10SFC	10" Sediment Filter Cartridge	HG20SFC	20" Sediment Filter Cartridge	HG10SFC	10" Sediment Filter Cartridge	HG20SFC	20" Sediment Filter Cartridge
HG10CTOFC	10" CTO Filter Cartridge	HG20CTOFC	20" CTO Filter Cartridge	HG10CTOFC	10" CTO Filter Cartridge	HG20CTOFC	20" CTO Filter Cartridge
				HGUVQSS		UV Quartz Sleeve and Seals	
				HGBPC		UV Ballast and power cord	
				HGUVL		UV Lamp	

WOFLC*	Watts OneFlow Limescale Cartridge
---------------	-----------------------------------

*Indent only